

High Power Portable 18Bands Jammer/Blocker

SA-PJ18

Brief Description:

Sacontelecom portable jammer PJ18 its latest model in market , fits handheld using. it can effectively block CDMA,GSM,3G UMTS,4G LTE, 5G cellphone ,GPS,Wi-Fi/Bluetooth ,Lojack ,Remote control ,VHF/UHF radio , it could block all types of Android phones, Tablets, Smart Phones, iPhones, Win phones walkie -talkie etc.This portable jammer could work for wireless 2G, 3G, 4G, WiMax, Wi-Fi, Bluetooth ,GPS Lojack, remote control ,VHF/UHF Radio signals ,you could choose this model that will be work stably and reliably.The blocker could create a quiet zone around you and prevent leaking of information in sensitive areas.



1	ON/OFF Switch
2	Single band control switch
3	Input DC
4	Wind slots in both sides
5	Power indicator
6	LED lights for Charging
7	Antenna
8	Nnber of antenna port
9	Inside cooling fans support Jammer working 24/7 continuously
10	Screen of battery status& working status

Features:

- * Covers eighttteen frequency bands Jamming all type wireless device
- * Compact Size and easy carry
- * Each band can turn ON/OFF without influencing the other bands operation
- * Rechargeable powerful battery and can be used outdoors
- * Good cooling system no Nosie can working long time
- * Could be used in Vehicle directly, With car charger for mobile using
- * Support use while battery charging
- * Only interfering downlink and no interception on the base station.

Applicable place:

For car, truck, bus, van, or even boat security, stop GPS tracking devices
 For meeting rooms, conference rooms, museums, galleries, theatres, concert halls, churches, temples, restaurants, classrooms, training centers, factories, banks, hospitals.



Specification:

Total Output Power: 16Watt

Cover Radius: 0-25m(under Signal level $\leq -85\text{dBm}$)@according to the signal density mobile network

Jamming type: Sweep Jamming

Antenna Type: 2dBi gain omni-directional antenna

Power Supply: Rechargeable lithium Battery /AC adapter (50 to 60Hz/100 to 240V AC –DC12V) and 12V car charger

Built-in Rechargeable lithium Battery:12000mAh

Working time of Battery: 2.5Hours

Electric Filed (SAR):Compatible with ICNIRP Standards(Human safe)

Operating Temp:-20 to +50 °C

Storage Temp:-40 to +60 °C

Humidity: 5%-80%

Dimension(LXWXH): 190 x 126 x 46mm not include antennas

Packing size dimension:330x250x80mm

weight:2kg

Order Information:

Item no :PJ18 Jamming for 2G/CDMA/GSM/3G/4GLTE Cellphone/Wi-Fi /Bluetooth2.4G/5G/ UHF/VHF Walkie-Talkie lojack/XM Radio/GPSL1-L5/RF433/434/315/868

America Type frequency for United States, Canada, Mexico ,S. America.

America Type frequency for United States, Canada, Mexico ,S. America.

CH1. 5G 617-685MHz 1W

CH2 5G 3400 3400-3600MHz 1W

CH3. GPS/Glonass/GALILEOL1: 1570-1610MHz 1W

CH4 4G2300: 2300-2400 1W

CH5 WIFI5.2G : 5125-5350 1W

CH6 GPS/ Glonass/GALILEOLGPSL L2 /1170-1280 1W

CH7 5G 1710-1780 1W

CH8 4G2600:2570-2690 1W

CH9 VHF/LOJACK: 135-175 1W

CH10 5G3600 3600-3900 1W

CH11 RC315 1W

CH12 4G700:700-803 1W

CH13 3G/WCDMA/UMTS :2110-2170 1W

CH14 RC 433 1W

CH15 CDMA/IDEN/800/850/868: 850-894MHz 1W

CH16 PCS1900 or GPSL3L4: 1900-1990 or 1370-1390MHz 1W

CH17 WIFI2.4G: 2400-2500 1W

CH18 WIFI5.8G:5725-5850 1W

Europe Type frequency for Europe, Asia, Australia, Middle East,

CH1. UHF 400-470MHz 1W

CH2 5G 3400 3400-3600MHz 1W

CH3. GPS/Glonass/GALILEOL1: 1570-1610MHz 1W

CH4 4G2300: 2300-2400 1W

CH5 WIFI5.2G : 5125-5350 1W

CH6 GPS/ Glonass/GALILEOLGPSL L1 /1170-1280 1W

CH7 5G 1470-1518MHz 1W

CH8 4G2600:2570-2690 1W

CH9 VHF/LOJACK: 135-175 1W

CH10 WIFI2.4G: 2400-2500 1W

CH11 RC315 1W

CH12 4G700:758-826 1W

CH13 3G/WCDMA/UMTS :2110-2170 1W

CH14 RC 433 1W

CH15 GSM900 :925-960 1W

CH16 DCS/PCS 4GLTE1800: 1805-1880 1W

CH17 5G3600 3600-3900 1W

CH18 WIFI5.8G:5725-5850 1W



Package contents:

Main unit x 1pcs

Nylon cover x1pcs

Power adapter x1pcs

Car charger x 1pcs

Omni antenna x 16pcs

